```
:ASM

                1000 ********************
                1010 * DJMP TO BALLY
                1020 * ARCADE FROM AN        SYMBOL TABLE
                1030 * APPLE II
                1040 *                        WAIT   FCA8   TAPE   C020   ASTO   00F9
                1050 * (C) 1981 WISEMAN
                1060 ********************     BADA   5000   AIL    00FA   AIH    00FB
                1070 WAIT .EQ $FCA8
                1080 TAPE .EQ $C020           STAR   4800   LOOP   480A   DJWR   4814
                1090 ASTO .EQ $F9
                1100 BADA .EQ $5000           DONE   481C   WRIT   481D   HEAD   481F
                1110 AIL  .EQ $FA
                1120 AIH  .EQ $FB             TBT0   482A   B48A   4934   TBT1   4937
                1130      .OR $4800
                1140 ********************     HZ48   4841   HZ4A   4843   HZ12   484F
4800- A9 50      1150 STAR LDA #$50
4802- 85 FB      1160      STA AIH            HZ1A   4851
4804- A9 00      1170      LDA #$00
4806- 85 FA      1180      STA AIL
4808- A0 00      1190      LDY #$00
480A- B1 FA      1200 LOOP LDA (AIL),Y       4800- A9 50 85 FB A9 00 85 FA
480C- F0 0E      1210      BEQ DONE          4808- A0 00 B1 FA F0 0E E6 FA
480E- E6 FA      1220      INC AIL           4810- D0 02 E6 FB 85 F9 20 1D
4810- D0 02      1230      BNE DOWR          4818- 48 4C 0A 48 60 A0 05 20
4812- E6 FB      1240      INC AIH           4820- 4F 48 88 D0 FA A0 08 20
4814- 85 F9      1250 DOWR STA ASTO          4828- 4F 48 46 F9 B0 06 20 4F
4816- 20 1D 48   1260      JSR WRIT          4830- 48 4C 37 48 20 41 48 88
4819- 4C 0A 48   1270      JMP LOOP          4838- D0 F0 20 41 48 20 41 48
481C- 60         1280 DONE RTS              4840- 60 A2 10 A9 06 20 A8 FC
                1290 ********************     4848- AD 20 C0 CA D0 F5 60 A2
                1300 * WRITE A BYTE          4850- 08 A9 10 20 A8 FC AD 20
481D- A0 05      1310 WRIT LDY #$05          4858- C0 CA D0 F5 60 FF 00 00
481F- 20 41 48   1320 HEAD JSR HZ48
4822- 88         1330      DEY
4823- D0 FA      1340      BNE HEAD
4825- A0 08      1350      LDY #$08
4827- 20 4F 48   1360      JSR HZ12
482A- 46 F9      1370 TBT0 LSR ASTO
482C- B0 06      1380      BCS B48A
482E- 20 4F 48   1390      JSR HZ12
4831- 4C 37 48   1400      JMP TBT1
4834- 20 41 48   1410 B48A JSR HZ48
4837- 88         1420 TBT1 DEY
4838- D0 F0      1430      BNE TBT0
483A- 20 41 48   1440      JSR HZ48
483D- 20 41 48   1450      JSR HZ48
4840- 60         1460      RTS
                1470 ********************
**
                1490 * WRITE THE TONES
4841- A2 10      1490 HZ48 LDX #$10
4843- A9 06      1500 HZ4A LDA #$06
4845- 20 A8 FC   1510      JSR WAIT
4848- AD 20 C0   1520      LDA TAPE
484B- CA         1530      DEX
484C- D0 F5      1540      BNE HZ4A
484E- 60         1550      RTS
484F- A2 08      1560 HZ12 LDX #$08
4851- A9 10      1570 HZ1A LDA #$10
4853- 20 A8 FC   1580      JSR WAIT
4856- AD 20 C0   1590      LDA TAPE
4859- CA         1600      DEX
485A- D0 F5      1610      BNE HZ1A
485C- 60         1620      RTS
```

```
               1000 ********************

               1010 * LOAD FROM BALLY
               1020 *    TO APPLE
               1030 *
               1040 * (C) 1981 WISEMAN
               1050 ********************

               1060 TAPE .EQ $C060
               1070 INPT .EQ $5000
               1080 LAST .EQ $F9
               1090 CNTR .EQ $FB
               1100 BYTE .EQ $FC
               1110 SPKR .EQ $C030
               1120 AIL  .EQ $FD
               1130 AIH  .EQ $FE
               1140      .OR $4600
               1150 ********************
4600- A9 00    1160 STAR LDA #$00
4602- 85 FD    1170      STA AIL
4604- A9 50    1180      LDA #$50
4606- 85 FE    1190      STA AIH
4608- A0 00    1200      LDY #$00
460A- 20 26 46 1210 NEXT JSR GBYT
460D- A5 FC    1220      LDA BYTE
460F- 91 FD    1230      STA (AIL),Y
4611- 2C 30 C0 1240      BIT SPKR
4614- E6 FD    1250      INC AIL
4616- D0 02    1260      BNE GTST
4618- E6 FE    1270      INC AIH
461A- C9 5C    1280 GTST CMP #$5C
461C- F0 03    1290      BEQ QUIT
461E- 4C 0A 46 1300      JMP NEXT
4621- A9 00    1310 QUIT LDA #$00
4623- 91 FD    1320      STA (AIL),Y
4625- 60      1330      RTS
               1340 ********************

               1350 * GET A BYTE
4626- A9 00    1360 GBYT LDA #$00
4628- 85 FB    1370      STA CNTR
462A- A9 50    1380      LDA #$80
462C- 85 FC    1390      STA BYTE
462E- 20 78 46 1400      JSR RDBI
4631- 20 78 46 1410 HEAF JSR RDBI
4634- E0 15    1420      CPX #$15
4636- B0 F9    1430      BCS HEAF
4638- 20 78 46 1440 HEAD JSR RDBI
463B- E0 15    1450      CPX #$15
463D- 90 F9    1460      BCC HEAD
463F- 20 60 46 1470      JSR BTT0
4642- 20 78 46 1480 TEST JSR RDBI
4645- E0 15    1490      CPX #$15
4647- 90 0B    1500      BCC GOT1
4649- 18      1510 GOTO CLC
464A- 66 FC    1520      ROR BYTE
464C- B0 11    1530      BCS DONE
464E- 20 60 46 1540      JSR BTT0
4651- 4C 42 46 1550      JMP TEST
4654- 38      1560 GOT1 SEC
4655- 66 FC    1570      ROR BYTE
4657- B0 06    1580      BCS DONE
4659- 20 6C 46 1590      JSR BTT1
465C- 4C 42 46 1600      JMP TEST
465F- 60      1610 DONE RTS
               1620 ********************

               1630 * GET A BIT
4660- A2 07    1640 BTT0 LDX #$07
4662- 86 FB    1650      STX CNTR
4664- 20 78 46 1660 BTL0 JSR RDBI
4667- C6 FB    1670      DEC CNTR
4669- D0 F9    1680      BNE BTL0
466B- 60      1690      RTS
466C- A2 0F    1700 BTT1 LDX #$0F
466E- 86 FB    1710      STX CNTR
4670- 20 78 46 1720 BTL1 JSR RDBI
4673- C6 FB    1730      DEC CNTR
4675- D0 F9    1740      BNE BTL1
4677- 60      1750      RTS
               1760 ********************

               1770 * GET TONE CYCLE
4678- A2 00    1780 RDBI LDX #$00
467A- E8      1790 LOOP INX
467B- AD 60 C0 1800      LDA TAPE
467E- 45 F9    1810      EOR LAST
4680- 10 F8    1820      BPL LOOP
4682- 45 F9    1830      EOR LAST
4684- 85 F9    1840      STA LAST
4686- 8A      1850      TXA
4687- 60      1860      RTS


SYMBOL TABLE

TAPE C060   INPT 5000   LAST 00F9

CNTR 00FB   BYTE 00FC   SPKR C030

AIL  00FD   AIH  00FE   STAR 4600

NEXT 460A   QTST 461A   QUIT 4621

GBYT 4626   HEAF 4631   HEAD 4638

TEST 4642   GOTO 4649   GOT1 4654

DONE 465F   BTT0 4660   BTL0 4664

BTT1 466C   BTL1 4670   RDBI 4678

LOOP 467A

:
:$4600.4687

4600- A9 00 85 FD A9 50 85 FE
4608- A0 00 20 26 46 A5 FC 91
4610- FD 2C 30 C0 E6 FD D0 02
4618- E6 FE C9 5C F0 03 4C 0A
4620- 46 A9 00 91 FD 60 A9 00
4628- 85 FB A9 80 85 FC 20 78
4630- 46 20 78 46 E0 15 B0 F9
4638- 20 78 46 E0 15 90 F9 20
4640- 60 46 20 78 46 E0 15 90
4648- 0B 18 66 FC B0 11 20 60
4650- 46 4C 42 46 38 66 FC B0
4658- 06 20 6C 46 4C 42 46 60
4660- A2 07 86 FB 20 78 46 C6
4668- FB D0 F9 60 A2 0F 86 FB
4670- 20 78 46 C6 FB D0 F9 60
4678- A2 00 E8 AD 60 C0 45 F9
4680- 10 F8 45 F9 85 F9 8A 60
```

```
              1000 ****************
              1010 * KEYBOARD ENTRY
              1020 *
              1030 * APPLE KEYBOARD
              1040 * TO BALLY ARCADE
              1050 *
              1060 * (C) 1981 WISEMAN
              1070 ****************
              1080 LAST .EQ $FE
              1090 THIS .EQ $FF
              1100 KEYB .EQ $C000
              1110 KEYR .EQ $C010
              1120 PROG .EQ $5000
              1130 SEND .EQ $4800
              1140      .OR $4400
              1150 ****************
4400- A0 00   1160 STAR LDY #$00
4402- 8C 6B 45 1170      STY PRSW
4405- 8C 00 50 1180 LOOP STY PROG
4408- 8C 01 50 1190      STY PROG+1
440B- 8C 02 50 1200      STY PROG+2
440E- 20 62 45 1210      JSR KEYI
4411- C9 DE   1220      CMP #$DE
4413- F0 2D   1230      BEQ QUIT
4415- C9 83   1240      CMP #$83
4417- F0 29   1250      BEQ SERA
4419- C9 AA   1260      CMP #$AA
441B- F0 2A   1270      BEQ SMLT
441D- C9 BF   1280      CMP #$BF
441F- F0 2B   1290      BEQ SDIV
4421- C9 A2   1300      CMP #$A2
4423- F0 2C   1310      BEQ SQOT
4425- C9 8D   1320      CMP #$8D
4427- F0 33   1330      BEQ SRET
4429- 49 80   1340 EXCL EOR #$80
442B- 85 FF   1350      STA THIS
442D- CC 6B 45 1360      CPY PRSW
4430- D0 04   1370      BNE GOTL
4432- C9 41   1380      CMP #$41
4434- B0 2C   1390      BCS CHEK
4436- 85 FE   1400 GOTL STA LAST
4438- 8D 00 50 1410 XGFF STA PROG
443B- 20 00 48 1420      JSR SEND
443E- 4C 05 44 1430      JMP LOOP
4441- 60      1440 QUIT RTS
              1450 ****************
              1460 * SPECIAL CHARACTERS
4442- A9 1F   1470 SERA LDA #$1F
4444- 4C 36 44 1480      JMP GOTL
4447- A9 62   1490 SMLT LDA #$62
4449- 4C 36 44 1500      JMP GOTL
444C- A9 63   1510 SDIV LDA #$63
444E- 4C 36 44 1520      JMP GOTL
4451- CC 6B 45 1530 SQOT CPY PRSW
4454- D0 06   1540      BNE SRET
4456- EE 6B 45 1550      INC PRSW
4459- 4C 29 44 1560      JMP EXCL
445C- 8C 6B 45 1570 SRET STY PRSW
445F- 4C 29 44 1580      JMP EXCL
              1590 ****************
4462- A5 FE   1600 CHEK LDA LAST
4464- C9 41   1610      CMP #$41
4466- B0 05   1620      BCS TEST
4468- A5 FF   1630 CHKD LDA THIS
446A- 4C 36 44 1640      JMP GOTL
```

```
              1650 ****************
              1660 * TWO LETTERS TOGTHR
446D- 20 73 44 1670 TEST JSR CMB0
4470- 4C 68 44 1680      JMP CHKD
              1690 ****************
              1700 * CHECK COMBO'S
4473- C9 49   1710 CMB0 CMP #$49
4475- F0 32   1720      BEQ GINI
4477- 90 11   1730      BCC CMB1
4479- C9 50   1740      CMP #$50
447B- F0 37   1750      BEQ GINP
447D- 90 1C   1760      BCC CMB2
447F- C9 53   1770      CMP #$53
4481- F0 38   1780      BEQ GINS
4483- 90 1F   1790      BCC CMB3
4485- C9 54   1800      CMP #$54
4487- F0 39   1810      BEQ GINT
4489- 60      1820      RTS
448A- C9 47   1830 CMB1 CMP #$47
448C- F0 3B   1840      BEQ GING
448E- C9 42   1850      CMP #$42
4490- F0 42   1860      BEQ GINB
4492- C9 43   1870      CMP #$43
4494- F0 45   1880      BEQ GINC
4496- C9 46   1890      CMP #$46
4498- F0 48   1900      BEQ GINF
449A- 60      1910      RTS
449B- C9 4C   1920 CMB2 CMP #$4C
449D- F0 4A   1930      BEQ GINL
449F- C9 4E   1940      CMP #$4E
44A1- F0 51   1950      BEQ GINN
44A3- 60      1960      RTS
44A4- C9 52   1970 CMB3 CMP #$52
44A6- F0 53   1980      BEQ GINR
44A8- 60      1990      RTS
              2000 ****************
              2010 * TEST SECOND LETTER
44A9- A5 FF   2020 GINI LDA THIS
44AB- C9 46   2030      CMP #$46
44AD- F0 5B   2040      BEQ SIF
44AF- C9 4E   2050      CMP #$4E
44B1- F0 5C   2060      BEQ SIN
44B3- 60      2070      RTS
44B4- A5 FF   2080 GINP LDA THIS
44B6- C9 52   2090      CMP #$52
44B8- F0 5A   2100      BEQ SPR
44BA- 60      2110      RTS
44BB- A5 FF   2120 GINS LDA THIS
44BD- C9 54   2130      CMP #$54
44BF- F0 58   2140      BEQ SST
44C1- 60      2150      RTS
44C2- A5 FF   2160 GINT LDA THIS
44C4- C9 4F   2170      CMP #$4F
44C6- F0 56   2180      BEQ STO
44C8- 60      2190      RTS
44C9- A5 FF   2200 GING LDA THIS
44CB- C9 4F   2210      CMP #$4F
44CD- F0 50   2220      BEQ SGO
44CF- C9 53   2230      CMP #$53
44D1- F0 55   2240      BEQ SGS
44D3- 60      2250      RTS
44D4- A5 FF   2260 GINB LDA THIS
44D6- C9 4F   2270      CMP #$4F
44D8- F0 53   2280      BEQ SBO
44DA- 60      2290      RTS
44DB- A5 FF   2300 GINC LDA THIS
```

```
44DD- C9 4C    2310        CMP #$4C
44DF- F0 51    2320        BEQ SCL
44E1- 60       2330        RTS
44E2- A5 FF    2340 GINF LDA THIS
44E4- C9 4F    2350        CMP #$4F
44E6- F0 4F    2360        BEQ SFO
44E8- 60       2370        RTS
44E9- A5 FF    2380 GINL LDA THIS
44EB- C9 49    2390        CMP #$49
44ED- F0 4D    2400        BEQ SLI
44EF- C9 53    2410        CMP #$53
44F1- F0 4E    2420        BEQ SLS
44F3- 60       2430        RTS
44F4- A5 FF    2440 GINN LDA THIS
44F6- C9 45    2450        CMP #$45
44F8- F0 4C    2460        BEQ SNE
44FA- 60       2470        RTS
44FB- A5 FF    2480 GINR LDA THIS
44FD- C9 45    2490        CMP #$45
44FF- F0 4A    2500        BEQ SRE
4501- C9 4E    2510        CMP #$4E
4503- F0 4B    2520        BEQ SRN
4505- C9 55    2530        CMP #$55
4507- F0 4C    2540        BEQ SRU
4509- 60       2550        RTS
               2560 ****************
               2570 * SEND BALLY WORD
450A- A9 6D    2580 SIF  LDA #$6D
450C- 4C 5A 45 2590        JMP ERA
450F- A9 73    2600 SIN  LDA #$73
4511- 4C 5A 45 2610        JMP ERA
4514- A9 74    2620 SPR  LDA #$74
4516- 4C 5A 45 2630        JMP ERA
4519- A9 75    2640 SST  LDA #$75
451B- 4C 5A 45 2650        JMP ERA
451E- A9 77    2660 STO  LDA #$77
4520- 4C 5A 45 2670        JMP ERA
4523- A9 6E    2680 SGO  LDA #$6E
4525- 4C 5A 45 2690        JMP ERA
4528- A9 6F    2700 SGS  LDA #$6F
452A- 4C 5A 45 2710        JMP ERA
452D- A9 71    2720 SBO  LDA #$71
452F- 4C 5A 45 2730        JMP ERA
4532- A9 69    2740 SCL  LDA #$69
4534- 4C 5A 45 2750        JMP ERA
4537- A9 72    2760 SFO  LDA #$72
4539- 4C 5A 45 2770        JMP ERA
453C- A9 6C    2780 SLI  LDA #$6C
453E- 4C 5A 45 2790        JMP ERA
4541- A9 68    2800 SLS  LDA #$68
4543- 4C 5A 45 2810        JMP ERA
4546- A9 6B    2820 SNE  LDA #$6B
4548- 4C 5A 45 2830        JMP ERA
454B- A9 70    2840 SRE  LDA #$70
454D- 4C 5A 45 2850        JMP ERA
4550- A9 76    2860 SRN  LDA #$76
4552- 4C 5A 45 2870        JMP ERA
4555- A9 6A    2880 SRU  LDA #$6A
4557- 4C 5A 45 2890        JMP ERA
               2900 ******
455A- 8D 01 50 2910 ERA  STA PROG+1
455D- A9 1F    2920        LDA #$1F
455F- 85 FF    2930        STA THIS
4561- 60       2940        RTS
               2950 ****************
               2960 * KEYBOARD INPUT
4562- AD 00 C0 2970 KEYI LDA KEYB
4565- 10 FB    2980        BPL KEYI
4567- 2C 10 C0 2990        BIT KEYR
456A- 60       3000        RTS
456B- 00       3010 PRSW .HS 00
```

SYMBOL TABLE

LAST	00FE	THIS	00FF	KEYB	C000
KEYR	C010	PROG	5000	SEND	4300
STAR	4400	LOOP	4405	EXCL	4429
GOTL	4436	XCFF	4438	QUIT	4441
SERA	4442	SMLT	4447	SDIV	444C
SQOT	4451	SRET	445C	CHEK	4462
CHKD	4468	TEST	446D	CMB0	4473
CMB1	448A	CMB2	449B	CMB3	44A4
GINI	44A9	GINP	44B4	GINS	44BB
GINT	44C2	GING	44C9	GINB	44D4
GINC	44DB	GINF	44E2	GINL	44E9
GINN	44F4	GINR	44FB	SIF	450A
SIN	450F	SPR	4514	SST	4519
STO	451E	SGO	4523	SGS	4528
SBO	452D	SCL	4532	SFO	4537
SLI	453C	SLS	4541	SNE	4546
SRE	454B	SRN	4550	SRU	4555
ERA	455A	KEYI	4562	PRSW	456B

```
4400- A0 00 8D 6B 45 8C 00 50
4408- 8C 01 50 8C 02 50 20 62
4410- 45 C9 DE F0 2C C9 83 F0
4418- 29 C9 AA F0 2A C9 BF F0
4420- 2B C9 A2 F0 2C C9 8D F0
4428- 33 49 80 85 FF CC 6B 45
4430- D0 04 C9 41 B0 CC 85 FE
4438- 8D 00 50 20 00 45 4C 05
4440- 44 60 A9 1F 4C 36 44 A9
4448- 62 4C 36 44 A9 63 4C 36
4450- 44 CC 6B 45 D0 06 EE 6B
4458- 45 4C 29 44 8C 6B 45 4C
4460- 29 44 A5 FE C9 41 B0 05
4468- A5 FF 4C 36 44 20 73 44
4470- 4C 6B 44 C9 49 F0 32 90
4478- 11 C9 50 F0 37 90 1C C9
4480- 53 F0 33 90 1F C9 54 F0
4488- 39 60 C9 47 F0 3B C9 42
4490- F0 42 C9 43 F0 45 C9 46
4498- F0 48 60 C9 4C F0 4A C9
44A0- 4E F0 51 60 C9 52 F0 53
44A8- 60 A5 FF C9 46 F0 5B C9
44B0- 4E F0 5C 60 A5 FF C9 52
44B8- F0 5A 60 A5 FF C9 54 F0
44C0- 58 60 A5 FF C9 4F F0 56
44C8- 60 A5 FF C9 4F F0 54 C9
44D0- 53 F0 55 60 A5 FF C9 4F
44D8- F0 53 60 A5 FF C9 4C F0
44E0- 51 60 A5 FF C9 4F F0 4F
44E8- 60 A5 FF C9 49 F0 4D C9
44F0- 53 F0 4E 60 A5 FF C9 45
44F8- F0 4C 60 A5 FF C9 45 F0
4500- 4A C9 4E F0 4B C9 55 F0
4508- 4C 60 A9 6D 4C 5A 45 A9
4510- 73 4C 5A 45 A9 74 4C 5A
4518- 45 A9 75 4C 5A 45 A9 77
4520- 4C 5A 45 A9 6E 4C 5A 45
4528- A9 6F 4C 5A 45 A9 71 4C
4530- 5A 45 A9 67 4C 5A 45 A9
4538- 72 4C 5A 45 A9 6C 4C 5A
4540- 45 A9 68 4C 5A 45 A9 6B
4548- 4C 5A 45 A9 70 4C 5A 45
4550- A9 76 4C 5A 45 A9 6A 4C
4558- 5A 45 8D 01 50 A9 1F 85
4560- FF 60 AD 00 C0 10 FB 2C
4568- 10 C0 60 00
```

```
                    1000 ****************
                    1010 * PRINT BALLY ARCADE

                    1020 * TINY BASIC ON AN
                    1030 * APPLE II
                    1040 *
                    1050 * (C) 1981 WISEMAN
                    1060 ****************
                    1070 COUT  .EQ $FE
                    1080 AIH   .EQ $FF
                    1090 COUT  .EQ $FDED
                    1100 KEYB  .EQ $C000
                    1110 KEYR  .EQ $C010
                    1120       .OR $4200
                    1130 ****************
4200- A9 50         1140 STAR LDA #$50
4202- 95 FF         1150      STA AIH
4204- A0 00         1160      LDY #$00
4206- 84 FE         1170      STY AIL
4208- AD 00 C0      1180 GETC LDA KEYB
420B- 10 08         1190      BPL GTCC
420D- 2C 10 C0      1200      BIT KEYR
4210- AD 00 C0      1210 HANG LDA KEYB
4213- 10 FB         1220      BPL HANG
4215- 2C 10 C0      1230      BIT KEYR
4218- B1 FE         1240 GTCC LDA (AIL),Y
421A- D0 01         1250      BNE GOTC
421C- 60            1260      RTS
421F- 49 80         1270 AIL  EOR #$80
421F- C9 DB         1280 GOTC CMP #$DB
4221- B0 0C         1290      BCS FRWD
4223- 20 ED FD      1300      JSR COUT
4226- E6 FE         1310 NEXT INC AIL
4228- D0 DE         1320      BNE GETC
422A- E6 FF         1330      INC AIH
422C- 4C 08 42      1340      JMP GETC
                    1350 ****************
********
                    1360 * HANDLE SPECIAL WO
RDS
                    1370 ****************
********
422F- E9 DA         1380 FRWD SBC #$DA
4231- 8D 51 42      1390      STA HOLA
4234- A2 00         1400      LDX #$00
4236- BD 52 42      1410 LOOP LDA WRDS,X
4239- E8            1420      INX
423A- C9 A0         1430      CMP #$A0
423C- D0 F8         1440      BNE LOOP
423E- CE 51 42      1450      DEC HOLA
4241- D0 F3         1460      BNE LOOP
4243- BD 52 42      1470 PRLP LDA WRDS,X
4246- E8            1480      INX
4247- 20 ED FD      1490      JSR COUT
424A- C9 A0         1500      CMP #$A0
424C- D0 F5         1510      BNE PRLP
424E- 4C 26 42      1520      JMP NEXT
```

```
4251- 00            1530 HOLA .HS 00
4252- A0 A8 A0
4255- AF AC A9
4258- A0 1E A0
425B- BF A0 BF
425E- A0 BF         1540 WRDS .AS -" ( / ) †
? ? ?"
4260- A0 AA A0
4263- AF A0 BF
4266- A0 BF A0
4269- BF A0 BF      1550      .AS -" * / ? ?
? ?"
426C- A0 CC C9
426F- C3 CC C5
4272- C3 C1 D2
4275- C1 D2 A0
4278- D2 E5 CE      1560      .AS -" LIST CLE
AR RUN"
427B- A0 CE C5
427E- 1B E4 A0
4281- CC C7 CE
4284- C5 A0 C9
4287- C6 A0 C7
428A- CF D4 CF      1570      .AS -" NEXT LIN
E IF GOTO"
428D- A0 C7 CF
4290- D3 D5 C2
4293- A0 D2 C5
4296- D4 D5 D2
4299- CE A0 C2
429C- CF D8         1580      .AS -" GOSUB RE
TURN BOX"
429F- A0 C6 CF
42A1- D2 A0 C9
42A4- CE E0 D5
42A7- D4 A0 D0
42AA- D2 C9 CE
42AD- D4            1590      .AS -" FOR INPU
T PRINT"
42AE- A0 D3 D4
42B1- C5 D0 A0
42B4- D2 CE C4
42B7- A0 D4 CF
42BA- A0 BF A0
42BD- BF A0 BF
42C0- A0 BF A0
42C3- BF          1600      .AS -" STEP RND
TO ? ? ? ?"
42C4- A0 BF A0
42C7- BF A0 BF
42CA- A0 BF A0
42CD- BF A0 BF
42D0- A0 BF        1610      .AS -" ? ? ? ?
? ? ?"
```

```
SYMBOL TABLE

AIL    00FE   AIH    00FF   COUT   FDED

KEYB   C000   KEYR   C010   STAR   4200

GETC   4208   HANG   4210   GTCC   4218

GOTC   421D   NEXT   4226   PRWD   422F

LOOP   4236   FRLP   4243   HOLA   4251

WRDS   4252

:$4200.42D7

4200- A9 50 85 FF A0 00 84 FE
4208- AD 00 C0 10 0B CC 10 C0
4210- AD 00 C0 10 FB CC 10 C0
4218- B1 FE D0 01 60 49 80 C9
4220- DB B0 0C 20 ED FD E6 FE
4228- D0 DE E6 FF 4C 08 42 E9
4230- DA 8D 51 42 A2 00 BD 52
4238- 42 E8 C9 A0 D0 F3 CE 51
4240- 42 D0 F3 BD 52 42 E8 20
4248- ED FD C9 A0 D0 F5 4C 26
4250- 42 00 A0 A8 A0 AF A0 A9
4258- A0 DE A0 BF A0 EF A0 BF
4260- A0 AA A0 AF A0 BF A0 BF
4268- A0 BF A0 BF A0 CC C9 D3
4270- D4 A0 C3 CC C5 C1 D2 A0
4278- D2 D5 CE A0 CE C5 D8 D4
4280- A0 CC C9 CE C5 A0 C9 C6
4288- A0 C7 CF D4 CF A0 C7 CF
4290- D3 D5 C2 A0 D2 C5 D4 D5
4298- D2 CE A0 C2 CF D8 A0 C6
42A0- CF D2 A0 C9 CE D0 D5 D4
42A8- A0 D0 D2 C9 CE D4 A0 D3
42B0- D4 C5 D0 A0 D2 CE C4 A0
42B8- D4 CF A0 BF A0 BF A0 BF
42C0- A0 BF A0 BF A0 BF A0 BF
42C8- A0 BF A0 BF A0 BF A0 BF
42D0- A0 BF 00 00 FF FF 00 00
```

```
1   REM ***********************
2   REM * SAMPLE FILE HANDLER
3   REM * FOR USE WITH APPLE II
4   REM * BALLY ARCADE INTERFACE
5   REM *
6   REM * (C) 1981 WISEMAN
7   REM ***********************
8   B = 0:C = 0:D = 0:E = 0
10  HOME
15  D$ = CHR$ (4)
20  PRINT : PRINT : PRINT "BALLY
    ARCADE FILE HANDLER"
30  PRINT : PRINT "DO YOU WANT TO
    :"
40  PRINT : PRINT "   1. LOAD F
    ROM BALLY."
50  PRINT "   2. DUMP TO BALLY.
    "
55  PRINT "   3. CATALOG OF PRO
    GRAMS."
56  PRINT "   4. TYPE TO BALLY.
    "
57  PRINT "   5. LIST TINY BASI
    C PROGRAM."
59  PRINT "   6. QUIT."
60  GET A$: IF A$ = "1" THEN GOTO
    100
70  IF A$ = "2" THEN  GOTO 300
71  IF A$ = "3" THEN  PRINT : PRINT
    D$"CATALOG": PRINT : GOTO 20
74  IF A$ = "4" THEN  GOTO 500
75  IF A$ = "5" THEN  GOTO 600
80  END
95  REM ***********************
100 REM  LOAD FROM BALLY
101 REM ***********************
102 IF B THEN 120
105 PRINT D$
110 PRINT D$;"BLOAD LOAD FROM BA
    LLY ($4600)"
115 B = 1
120 PRINT "HIT RETURN WHEN YOU A
    RE READY"
130 GET A$
140 CALL 17920
150 A = PEEK (253) + 256 * PEEK
    (254) + 5
160 PRINT "LOAD COMPLETED"
170 PRINT : PRINT "DO YOU WANT T
    O SAVE THIS TO DISK? (Y/N)":
    GET A$
180 IF A$ = "N" THEN  GOTO 20
185 PRINT
190 PRINT "ENTER FILE NAME": INPUT
    A$
195 PRINT D$
200 PRINT D$;"BSAVE "A$",A$5000,
    L"A - 20480
210 PRINT : PRINT "COMPLETED": PRINT
    D$"CATALOG": GOTO 20
299 REM ***********************
```

```
300 REM  DUMP TO BALLY
301 REM ***********************
302 IF C THEN 320
305 PRINT D$
310 PRINT D$;"BLOAD DUMP TO BALL
    Y ($4800)"
315 C = 1
320 PRINT : PRINT "WHAT IS THE N
    AME OF THE PROGRAM?": INPUT
    A$
340 PRINT D$;"BLOAD "A$
345 PRINT
350 PRINT "HIT RETURN TO DUMP "A
    $
355 GET A$
360 CALL 18432
370 PRINT : PRINT "DUMP IS COMPL
    ETED": GOTO 20
496 REM ***********************
    *
497 REM  KEYBOARD TO BALLY
499 REM ***********************
500 IF C THEN 520
505 PRINT D$
510 PRINT D$;"BLOAD DUMP TO BALL
    Y ($4800)"
515 C = 1
517 IF D THEN 520
519 D = 1: PRINT D$: PRINT D$;"BL
    OAD TYPE TO BALLY ($4400)"
520 PRINT : PRINT "ENTER BALLY P
    ROGRAM": PRINT
530 CALL 17408
540 GOTO 20
599 REM ***********************
600 REM  PRINT BALLY PROGRAM
601 REM ***********************
610 PRINT : PRINT "IS PROGRAM LO
    ADED? (Y/N)"
620 GET A$: IF A$ = "Y" THEN  GOTO
    650
630 PRINT : PRINT "ENTER PROGRAM
    NAME": INPUT A$
635 PRINT D$
640 PRINT D$;"BLOAD "A$
650 IF E = 0 THEN  PRINT D$;"BLO
    AD PRINT BALLY ($4200)":E =
    1
660 CALL 16896: GOTO 20
```